Universal Keyboard Wedge Programming Guide

QS6000+ Universal Wedge USB Port Configuration

To configure your QS6000+ UW USB, follow these three steps:

1. Connect your QS6000+ cable to a USB port.
2. Find the Keyboard Country Code ID from Table 1 that matches your application.
3. Configure your scanner with the correct ID.

Table 1.

	KEYBOARD COUNTRY CODE ID TABLE											
OPERATING SYSTEM	UNITED STATES	FRANCE	DENMARK	SPAIN	GERMANY	BELGUIM	UNITED KINGDOM	NORWAY	ITALY	SWISS	POLAND	JAPAN
WIN 98 / XP / 2000	524	523	738	732	525	734	731	737	529	736	733	759
IMAC	527	526	746	741	528	742	740	745	530	744		

START

Enters Programming Mode.

ENABLE USB

Selects the Keyboard Country Code ID parameter for programming.

Use these labels to enter the Keyboard Country Code ID from Table 1.

1

2



3

4

5

6

7

8

9

0



END

Exit Programming Mode

R44-2443
(Rev. A)

© PSC Inc.

START and END Bar Codes

The bar codes on this page are used to enter and exit Universal Keyboard Wedge Programming Mode. For more information, see the topic titled "*How to Program Your Scanner*" in the *Introduction* section of this manual.

START

VARIABLE LENGTHS ENABLED

END